

# Jaguar



RX2-A/RX3-A

<b>Receiver T70RX2-A/RX3-A</b>	
Article number:	T70RX2-A; T70RX-09SB T70RX3-A; T70RX-15SB
Application areas:	Europe; Mobile and winch applications America and Asia; Mobile, winch and lifting applications
Frequency:	433 - 434 MHz (64 channels), 25 kHz channel spacing
Mod. Type:	Narrow band FM-modulation
Coding:	Digital pulse code
Code comb.:	Unique codes; 16.777.216
Relay output:	RX2-A; 9 relays                      RX3-A; 15 relays
Radio type:	Low IF receiver architecture
Sensitivity:	- 105 dBm at 1/1000 PER
Antenna:	External BNC
Power supply:	12-24V AC/DC, 48-230V AC
Power consumption:	7 - 300 mA
Temperature:	- 20° C to +55° C
Dimensions:	175 x 125 x 75 mm (6,89 x 4,92 x 2,95 in)
Protection:	IP 65
Recommended transmitter:	T70TX2-x

**TELE RADIO AB**  
Sweden, Main office  
Tel. +46 (0)31-748 54 60  
e-mail: info@tele-radio.com

www.tele-radio.com

**TELE RADIO SVERIGE**  
Sweden  
Tel. +46 (0)31-724 98 00  
e-mail: sverige@tele-radio.com

**TELE RADIO LTD**  
England  
Tel. +44 (0) 1625 509125  
e-mail: england@tele-radio.com

**TELE RADIO GmbH**  
Germany  
Tel. +49 (0)94 51-944 8 550  
e-mail: deutschland@tele-radio.com

**TELE RADIO LLC**  
North America & Latin America  
Tel. +1 (305) 459 0763  
e-mail: america@tele-radio.com

**TELE RADIO ASIA**  
China  
Tel. +86-(0)592-3111168  
e-mail: china@tele-radio.com

**TELE RADIO BV**  
Benelux  
Tel. +31-(0)70-419 41 20  
e-mail: benelux@tele-radio.com

**TELE RADIO TURKEY**  
Turkey  
Tel. +90 216 574 22 94  
e-mail: turkiye@tele-radio.com

**TELE RADIO AS**  
Norway  
Tel. +47-6933 4900  
e-mail: norge@tele-radio.com