

# Jaguar



T70TX2-A

T70TX2-B

T70TX2-E

<b>Transmitter T70TX2-*</b>	
Article number:	TX2-A; T70TX-08ERB-A TX2-B; T70TX-08ERB-B TX2-E; T70TX-08ERB-E
Application areas:	Europe; Mobile and winch applications America and Asia; Mobile, winch and lifting applications
Frequency:	433 - 434 MHz (64 channels), 25 KHz channel spacing
Mod. Type:	Narrowband FSK
Coding:	Digital pulse code
Code comb.:	Unique codes; 16.777.216
Functions:	Up to 16 functions
* = Foil:	A, B, E (see images above)
Output:	10 mW (by 50 ohm)
Antenna:	Built-in
Power supply:	3 Exchangeable 1,5V batteries type:AA
Power consumption:	Apr. 30 mA
Temperature:	-20° C to +55° C
Weight:	Apr. 300 g incl. batteries
Dimensions:	185 x 95 x 44 mm including rubber cover (7.28 x 3.75 x 1,73 in)
Protection:	IP 65
Recommended receiver:	T70RX2-A and T70RX3-A

**TELE RADIO AB**  
Sweden, Main office  
Tel. +46 (0)31-748 54 60  
e-mail: info@tele-radio.com

www.tele-radio.com

**TELE RADIO SVERIGE**  
Sweden  
Tel. +46 (0)31-724 98 00  
e-mail: sverige@tele-radio.com

**TELE RADIO LTD**  
England  
Tel. +44 (0) 1625 509125  
e-mail: england@tele-radio.com

**TELE RADIO GmbH**  
Germany  
Tel. +49 (0)94 51-944 8 550  
e-mail: deutschland@tele-radio.com

**TELE RADIO LLC**  
North America & Latin America  
Tel. +1 (305) 459 0763  
e-mail: america@tele-radio.com

**TELE RADIO ASIA**  
China  
Tel. +86-(0)592-3111168  
e-mail: china@tele-radio.com

**TELE RADIO BV**  
Benelux  
Tel. +31-(0)70-419 41 20  
e-mail: benelux@tele-radio.com

**TELE RADIO TURKEY**  
Turkey  
Tel. +90 216 574 22 94  
e-mail: turkiye@tele-radio.com

**TELE RADIO AS**  
Norway  
Tel. +47-6933 4900  
e-mail: norge@tele-radio.com